

This document provides additional assistance with wiring your Extron IP Link enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific Extron IP Link enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Video Projector
Manufacturer: Epson
Firmware Version: N/A
Model(s): EB-G5950NL, Powerlite Pro G5950NL, EB-C520XH, PowerLite Pro G5550

Minimum Software and Firmware Requirements:

IP Link Compiler	IP Link Firmware	GC Version
1.4.0	1.15	3.2.0

Version History:

Driver Version	Date	Notes
2	8/1/2011	Extron Certified. Added model Powerlite Pro G5550. Added error handling.
1	7/15/2011	Initial version. Extron Certified based on manufacturer info.

Driver Notes:

IP Link® Device Interface Ethernet Communication Sheet

Control Commands & States:

AV Mute	On	Off	
Input	Computer 1	Computer 2	BNC
	Video 1	Video 2	S-Video
	HDMI	USB	LAN
Power Control	On	Off	

Status Available:

AV Mute	On	Off	
Connection Status	Connected	Disconnected	
Device Status	Normal	Status Unavailable	Fan Error
	Error	Lamp Cover Error	Lamp Error
	Filter Error	Temp Error	
Input	Computer 1	Computer 2	BNC
	Video 1	Video 2	S-Video
	HDMI	USB	LAN
Lamp Usage	Hours		
Power Control	On	Off	
Power Status	On	Off	Warming Up
	Cooling Down	Status Unavailable	

Network communication:

When configuring the Ethernet driver, be sure device settings match that of the GC configuration.

Port Type:	Ethernet
Logon Credentials Supported:	No
Default Port:	4352
Multi-Connection Capable:	No
Port Changeable:	No

Ethernet Driver Configuration Description:

Please refer to user manual for settings and changes to the network communication parameters.

Notes for the Device: